


Tilt-Over Tubular Columns TPT Range

Technical Specification

Model Ref.	Height 'M'	Tilting rear clearance 'R'	Post Section 'P'	Pivot Section 'S1'	Door aperture 'H' x 'W'	Cable access hole Ø'C'	Maximum equip cap'ty	Weight Kgs.	Winch Selection
TP4T	4 mtr.	1150	120×120	Ø114	325 x 105	Ø108	25Kg.	92 Kgs.	WUA or WUB
TP5T	5 mtr.	1150	120×120	Ø114	325 x 105	Ø108	25Kg.	100Kgs.	WUA or WUB
TP6T	6 mtr.	1150	120×120	Ø114	325 × 105	Ø108	25Kg.	140Kgs.	WUA or WUB
TP8T	8 mtr.	1650	150×150	ø139	325 x 105	Ø140	25Kg.	305Kgs.	WUA
TP10T	10 mtr.	2150	200×200	ø193	325 x 105	Ø200	25Kg.	335Kgs.	WUA

All dimensions in mm unless otherwise stated

TPT/WUA Heavy Duty TPT/WUB Light Duty



Accessories & Adaptors

'FM' Root

TPT/ACB
TPT/Paint
TPT/SDA
TPT/SDA2
TPT/PTI-S2
TPT/TPTA
TPT/3SA
TPT/2SA
TPT/LSA

20

Anti-Climb Bracket
Paint to BS4800 & RAL Colours
Swept Dome Adaptor
Swept Dome Adaptor Dual
I Pan & Tilt c/w 2 Static Adaptors
Twin Pan & Tilt Adaptor
Triple Static Adaptor
Twin Static Adaptor
Pan & Tilt - Single Fixed

TPT/CS150-300 TPT/TBC TPT/HSD-F TPT/DB

'DB' Root

Optional

Column Spacers 150mm-300mm Telemetry Clamp Bracket High Security Door Option Decorative Banding

'FM' Root

8-Stud Fixing

Removable Winches


Although the WUA auto brake winch is initially more expensive, it has the versatility to cover the range of WEC products and has a quicker operating action.

Product Ref & Ordering Information

smartphone to access our

Operating Instructions and

Videos on our website!










Tilt-Over Tubular Columns TPT Range

Base and Windload Specification

Concrete Foundation Table X x Y x Z												
Model	11-1-6-1	A	rea of Cou	ntry	Area of Town							
Ref	Height	А	В	С	А	В	С					
TP4T	4 m	1.0×1.0× 0.5m Dp.	1.1×1.1× 0,55m Dp,	1.1×1.1× 0.55m Dp.	1.0×1.0× 0.5m Dp.	1.0×1.0× 0.5m Dp.	1.1×1.1× 0.55m Dp.					
TP5T	5m	1.0×1.0× 0.5m Dp.	1.1×1.1× 0.55m Dp.	1.1×1.1× 0.55m Dp.	1.0×1.0× 0.5m Dp.	1.0×1.0× 0.5m Dp.	1.1×1.1× 0.55m Dp.					
TP6T	6m	1.0×1.0× 0.5m Dp.	1.1×1.1× 0.55m Dp.	1.1×1.1× 0.55m Dp.	1.0×1.0× 0.5m Dp.	1.0×1.0× 0.5m Dp.	1.1×1.1× 0.55m Dp.					
TP8T	8m	1.2×1.2× 0.6m Dp.	1.3×1.3× 0.65m Dp.	1.3×1.3× 0.65m Dp.	1.1×1.1× 0.55m Dp.	1.2×1.2× 0.6m Dp.	1.3×1.3× 0.65m Dp.					
TP10T	10m	1.4×1.4× 0.7m Dp.	1.5×1.5× 0.75m Dp.	1.5×1.5× 0.75m Dp.	1.3×1.3× 0.65m Dp.	1.3×1.3× 0.65m Dp.	1.4×1.4× 0.7m Dp.					

A minimum soil bearing pressure of 75 KN/m2 is assumed





FM Root (FM)

4-hole fixing - up to 8m 8-hole fixing - 10m

fig. I

FM Root Assembly





Installation Method

- I. From the map, select location of installation
- 2. Excavate as per recommended area and depth
- 3. Assemble root base as shown in fig. I
- Insert root base into the hole ensuring that it is level and that the four studs protrude 60-70mm above the concrete foundation
- 5. Fit the cable duct if routing via the interior of the column. A plastic pipe of approximately 100mm outside diameter is recommended for this. Ensure this protrudes through the template by 50mm minimum.
- 6. Pour concrete ensuring that it is a mix of C35 to table 6 BS 8110 and then tamp down well
- 7. Fit the setting template over the four protruding studs, double-checking that they are level and that clear access can be gained to the cable duct if it is being used
- 8. Leave the concrete to cure for a minumum of 72 hours prior to attempting to erect the column
- When fitting the column, ensure that the concrete base is in complete contact with the underside of the column and grout accordingly
- 10. When the column has been fitted, protect the studs with a suitable protective coating. Denzo tape or similar is recommend for this

Foundation sizes are determined for three sets of wind speeds, which will cover most of the British Isles.

Area A = 44 m/s (98 mph)Area B = 48 m/s (107 mph)

Area C = 52m/s (116mph)

Maximum gust speed is likely to be exceeded on average once every 50 years at 10m above the ground in open level country.



